

AUM 027.TV - stainless steel washbasin with automatic tap AUM 3, with thermostatic valve



AUM 027 is a stainless washbasin of a modern design with a conical shape covering its waste. Supplied separately or completed with a sensor-controlled tap in all versions ? for premixed water, with a mixing or thermostatic valve. Feeding is possible from the mains through a safe source of power supply ZAC, or from 4 AA batteries. The washbasin is made of AISI 304 stainless steel. A recommended agent for stainless products maintenance: Würth ? preservation (order no. 0893 121 K), cleaning (order no. 893 121 1).

Rating: Not Rated Yet
[Ask a question about this product](#)

Manufacturer: [AZP Brno](#)

Description AUM 027 is a stainless washbasin of a modern design with a conical shape covering its waste. Supplied separately or completed with a sensor-controlled tap in all versions ? for premixed water, with a mixing or thermostatic valve. Feeding is possible from the mains through a safe source of power supply ZAC, or from 4 AA batteries. The washbasin is made of AISI 304 stainless steel. A recommended agent for stainless products maintenance: Würth ? preservation (order no. 0893 121 K), cleaning (order no. 893 121 1).
Complete delivery

- 1. st. steel washbasin
- 2. outlet
- 3. small fixing material

Requirements for setting up the construction

- 1. Prepared outlet d = 40 mm according to the scheme
- 2. Prepared water inlet G 1/2" according to the scheme (only for versions including tap)
- 3. Prepared el. supply cable 12 V, 50 Hz from source ZAC (CYKY 2A x 1,5) - only for 12 V versions

| | | | |
|-----------------------------|-------------------------------------|------------------|--|
| Basic technical information | | Radius of sensor | self-adjusting |
| | Water inlet | | G 1/2" |
| | Water outlet | | d = 40 mm |
| | Adjustable time of after-flow delay | | 0-4 s (adjusted to 1s) |
| | Water pressure | | 1 - 10 Bar (0,1 - 1,0 MPa) (12V verze) |
| | | | ZAC 1/36L (max. 6x AUM 027.1, AUM 027.TV; max. 4x AUM 027.2) |
| | Power supply | | 12 V, 50 Hz (AUM 027.1; AUM 027.2; AUM 027.TV) |
| | Power requirement | | 6 VA (AUM 027.1; AUM 027.TV) |
| | Source of power supply | | ZAC 1/20 (max. 3x AUM 027.1, AUM 027.TV; max. 2x AUM 027.2) |

Figures

